

### Setting reverse power 32R pick-up value for VAMP 230/255/257/259

The relay will show the pick-up value in input kilowatts, but the setting is done in percent of the nominal apparent power  $S_N$ .

$$S_N = CT_{Rated\ Primary} \cdot VT_{Rated\ Primary} \cdot \sqrt{3}$$

#### Example

Let us say that the pick-up target value for reverse power stage P< 32R is 5 % of the rated active input power of the motor.

Motor data:  
 Rated current  $I_{MOT} = 385\text{ A}$   
 Rated voltage  $U_{MOT} = 6000\text{ V}$   
 Power factor  $\cos\phi = 0.8$

Current and voltage transformers:  
 CT = 400/5  
 VT = 6600/120

First we calculate the nominal apparent power

$$S_N = 400 \cdot 6600 \cdot \sqrt{3} = 4572.6\text{ kVA}$$

and then the rated active input power

$$P_{Input} = I_{MOT} \cdot U_{MOT} \cdot \sqrt{3} \cdot \cos\phi = 3200.8\text{ kW}$$

The -5 % pick-up setting will be in input kilowatts

$$P_{Input\ Reverse} = -5\% \cdot P_{Input} = -0.05 \cdot 3200.8\text{ kW} = -160.04\text{ kW}.$$

The pick-up setting for the relay will be

$$P_{<Setting} = \frac{P_{Input\ Reverse}}{S_N} = -\frac{160.04}{4572.6} = -0.035 = -3.5\%.$$

VAMP Ltd  
 P.O.Box 810  
 FI-65101 VAASA  
 Finland  
 Visiting Address:  
 Vaasa Airport Park  
 Yrittäjänkatu 15  
 Vaasa, Finland  
 Tel: +358 20 753 3200  
 Fax: +358 20 753 3205  
 Email: [vamp@vamp.fi](mailto:vamp@vamp.fi)  
<http://www.vamp.fi>

We reserve the rights to product alterations without prior notice.  
 Copyright © Vamp Ltd. All trademarks are the property of their respective holders.



ISO 9001:2000  
 certified company

